

Allen-Bradley 1203-SSS Series B

Firmware Upgrade Instructions

January 14, 2002

UPGRADE CAN BE APPLIED TO:

Product Catalog #	1203-SSS Series B
Description	AnaCANda – DPI to RS232 DF1 Communications Module
Firmware	2.001 or later

REVISION INFORMATION AFTER UPGRADE IS APPLIED:

Product Revision	3.003
Application Program Firmware Revision	3.003.09
Boot Program Firmware Revision	3.003.09



IMPORTANT



Once a flash upgrade has been started, do not remove power from the DPI Host (e.g.; PowerFlex drive) until after the download has completed and the Diamond LED on the 1203-SSS becomes FLASHING GREEN. If power is removed before this occurs, the 1203-SSS may be permanently damaged. A 1203-SSS that has been damaged in this way cannot be repaired.

NOTE: This upgrade may cause the 1203-SSS parameters to revert to default values. You may want to save your configuration using DriveExplorer or DriveExecutive before upgrading.

HyperTerminal UPGRADE INSTRUCTIONS:

Use HyperTerminal to load the following files in the order listed:

1. 1203-SSS_3_003_09_Boot.bin
2. 1203-SSS_3_003_09_DPI.bin
3. 1203-SSS_3_003_09_SP.bin