

Allen-Bradley 1203-SSS Series B
Engineering Release Notes and Firmware Update Instructions
March 24, 2003

UPDATE CAN BE APPLIED TO:

Product Catalog #	1203-SSS Series B
Description	AnaCANda – DPI to RS232 DF1 Communications Module
Firmware	2.001 or later

REVISION INFORMATION AFTER UPDATE IS APPLIED:

Product Revision	3.004
Application Program Firmware Revision	3.004.06
Boot Program Firmware Revision	3.004.06



Once a flash update has been started, do not remove power from the DPI Host (e.g.; PowerFlex drive) until after the download has completed and the Diamond LED on the 1203-SSS becomes FLASHING GREEN. If power is removed before this occurs, the 1203-SSS may be permanently damaged. A 1203-SSS that has been damaged in this way cannot be repaired

NOTE: This update may cause the 1203-SSS parameters to revert to their default values. You may want to save your configuration using DriveExplorer or DriveExecutive before upgrading.

HyperTerminal UPDATE INSTRUCTIONS:

Use HyperTerminal to load the following files in the order listed:

1. 1203-SSS_3_004_06_Boot.bin
2. 1203-SSS_3_004_06_DPI.bin
3. 1203-SSS_3_004_06_SP.bin